

ALINCO

Quality. Style. Performance!

VHF FM HANDHELD TRANSCEIVER

DJ-W18



Power, Features, Convenience and Fun!

This new VHF handheld transceiver packs a lot of performance into a rugged body. Designed to comply IP67 dust/water proof, the DJ-W18 features clear, loud 1W audio output, 2.5ppm frequency stability, capable of operating 136-174MHz range at 5W in 200 programmable-channels or VFO*. In addition, DJ-W18 sports VHF AM aircraft and FM broadcast receiver for an extra listening pleasure and fun.

Keep in touch for retails, construction, factory, warehouse, in a theme-park, shopping mall, exhibition hall, hotel, park/mountain rangers and surveillance... where you need solid communications for business, the DJ-W18 is a reliable, cost effective alternative to a mobile/cell phone!

*VFO(frequency) mode may not be available due to regulation. Please consult with your dealer before purchase.

Features

- AM aircraft and FM broadcast receiver
- IP67 compatible Dust/water proof
- Plenty of operating time, with standard 1800 mAh Li-Ion battery pack
- Comes with a quick stand-charger that fill-up the empty battery in 4 hours
- Wide variety of selective calling features built-in; The 51 CTCSS, 1024 DCS, 4 Tone-burst tones
- Large, bright Alphanumeric Name tag LCD and easy-to-operate backlit keys
- VOX built-in
- 200 programmable channels
- 3 selectable output power 5/2/1W
- BCLO, DTMF Autodialer, Reverse, Talk-around, TOT functions and much more!



Specifications

GENERAL

DJ-W18	
Frequency Coverage	TX/RX : 136-174MHz Rx only : FM radio (76 - 107.95MHz) AM (118 - 135.99MHz)
Modulation	F3E(16K0F3E / 11K0F3E / RX only WFM,AM)
Frequency stability	±2.5ppm
Power supply requirement	7.4V (Battery)
Current drain (Approx.)	1500mA TX / 300mA receive at Max audio output 80mA squelched
Usable temperature range	-20~ +60°C(-4~140°F)
Channel step	2.5, 5, 6.25, 10, 12.5, 20, 25, 30 and 50 KHz
Dimensions	118 x 59 x 38mm (with battery pack)
Weight	approx.230g inclusive of battery pack and antenna

TRANSMITTER

Output Power (Approx)	Approx. 5W / 2W / 1W
Frequency Deviation	±5kHz / ±2.5kHz
Spurious emission	Less than -27dBm

RECEIVER

Receiver System	Direct conversion
Sensitivity (12dB SINAD Wide/Narrow)	Wide -12dBu / Narrow -9dBu
Adjacent Channel Selectivity	Wide More than 65dB Narrow More than 60dB
Audio output power	1W (10% distortion)

Specifications subject to change without notice or obligation.
Product intended for use by properly authorized operators.

Standard Accessories (A strap is included)

Whip antenna	Battery Pack	Rapid ChargerStand
EA-250	EBP-101 Li-ion 7.4V 1800mAh	EDC-219

AC Adapter	Belt Clip
EDC-220	EBC-51

Standard accessories declared herein are our factory default and may vary at moment of sales depending on the market and Dealers' sales policy.



Standard accessories

Options



● Earphone Microphone (EME-56A)



● Speaker Microphone (EMS-76)

Alinco and ALINCO logo are registered trademarks of Alinco Incorporated, Japan in the United States, EU States, Russia, China and many other countries. All other trademarks are the properties of their respective holders.

Authorized Dealer:

Copyright Alinco, Inc., Osaka, Japan. All rights reserved. Although Alinco has designed this brochure to be as accurate and comprehensive as possible, we reserve the right to make changes at any time to our equipment line, optional accessories, specifications, standard accessories, or availability of any such devices we manufacture and distribute. Please note that certain products and accessories may not be available in all countries of distribution therefore consult your Authorized Alinco Dealer for product availability and pricing. Colors of images herein may appear slightly different from actual products due to print.
* Projections are not included in the declared dimension values.